

GENERATING SET GE 6000 BS - PLUS

- Honda OHV gasoline engine
- Engine shut off-oil
- Three-phase asynchronous alternator
- Suitable for electronic equipment
- Wrap around protective frame
- Silenced
- Complies with EEC directives



Standard equipment 										
	Gasoline engine	Air cooling	Manual recoil	Engine shut down (oil)						
Options on request 										
	Asynchronous alternator	Voltmeter	Socket 400V EEC	Socket 230V EEC	Ground fault interrupter	Thermal shut off				
	● Plug 400V 16A 3PNT (T) ● Plug 230V 16A 2PT (M)				● Kit hour counter ● Earthing Kit MT10		● Trolley CTM200 ● Kit exhaust extension PS 4.5			

Technical Data

GE 6000 BS PLUS

A.C. GENERATION	50 Hz, asynchronous, three-phase, self-excited, self-regulated, brushless
Three-phase generation	6 kVA (4.8 kW) / 400 V / 8.7 A
Single-phase generation	5 kVA / 230 V / 21.7 A
Duty cycle	100%
Cos φ	0.8
Insulation class	H
On request other voltages and frequencies (60 Hz)	
ENGINE	Gasoline, 4-stroke, air cooled
Type	Honda GX 390
Output*	8.4 kW (11.4 HP)
Speed	3000 t/m
Displacement	389 cm ³
Cylinders	1
Fuel consumption	313 g/kWh
* Maximum output according to ISO 3046/1	
GENERAL SPECIFICATIONS	
Tank capacity	6.5 l
Running time (Load 75%)	3 h
Protection	IP 23
Dimensions Lxwxh (mm) *	870x525x590
Weight *	100 kg
Noise level **	99 LWA (74 dB(A) - 7 m)
* Dimensions and weight are inclusive of all parts without optional CTM. ** LWA conforms to EEC Directive 536	

Values shown are nominal values. For further information please contact the sales department.